

## LED-Netzgerät mit Konstantspannung, mit CASAMBI-Lichtsteuerung

LED power supply with constant voltage, with CASAMBI lighting control



**CBM002**

### Kodierschalterstellung Dip switch set

Betriebsart Operation mode	Leistung Power	Kodierschalterstellung Dip switch set					
		1	2	3	4	5	6
200 mA	9,6 W	-	ON	-	-	-	-
250 mA	12,0 W	-	ON	-	-	-	ON
300 mA	14,4 W	-	ON	-	-	ON	-
350 mA	16,8 W	-	ON	-	-	ON	ON
400 mA	18,0 W	-	ON	-	ON	-	-
450 mA	17,6 W	-	ON	-	ON	-	ON
500 mA	18,0 W	-	ON	-	ON	ON	-
550 mA	16,5 W	-	ON	-	ON	ON	ON
600 mA	18,0 W	-	ON	ON	-	-	-
650 mA	17,6 W	-	ON	ON	-	-	ON
700 mA	16,8 W	-	ON	ON	-	ON	-
750 mA	18,0 W	-	ON	ON	-	ON	ON
800 mA	16,8 W	-	ON	ON	ON	-	-
850 mA	17,9 W	-	ON	ON	ON	-	ON
900 mA	16,2 W	-	ON	ON	ON	ON	-
950 mA	17,1 W	-	ON	ON	ON	ON	ON
12 Vdc	11,4 W	ON	-	ON	ON	ON	ON
24 Vdc	18,0 W	-	-	ON	-	ON	ON

### Aufsatzstecker Typ Connector type

Europa  
Europe

Art.-Nr. 401474



UK  
UK

Art.-Nr. 401476



USA  
USA

Art.-Nr. 401475



Australien  
Australia

Art.-Nr. 401478

